

VESTA-141

HSGW-G8-4G-F1-868-ZW-DT-18 (ADC)



320-zone home security centre via radio with IP Ethernet connectivity + 4GLTe alarm



- 320-zone home security centre via radio with IP Ethernet connectivity
- Only compatible with 4G LTE alarm.com
- Supports RF 868-F1 and Z-Wave devices
- TCP/IP connectivity and alarm.com's 4G LTE module (optional WiFi pin)
- Amplified fast connection for external GPRS antenna (antenna not included)
- Bidirectional RF up to 2 km
- Integral solution with remote management
- Domotics and live supervision
- 8 partitions
- Sending reports via CID/SIA, Email, SMS, and Push
- iOS and Android App and web browser
- The VESTA radio control panel is compatible with Google Home and Alexa
- EN50131 Grade 2, Environmental Class II certified.



Reference / Model

VESTA-141 / HSGW-G8-4G-F1-868-ZW-DT-18 (ADC)

Specifications

320 radio zones
8 partitions
TCP/IP and 4G LTE communication from alarm.com (optional WiFi pin)
Incorporates alarm.com 4G LTE module
Only compatible with alarm.com
Supports RF 868-F1 and Z-Wave devices
Amplified quick connection for external GPRS antenna (not included, VESTA-274 recommended)
Reporting methods: CID/SIA, Email, SMS, Push Notification
Programming methods: Web and App
Live visual verification
Home automation
Energy management
24/7 emergency monitoring
Remote management
Built-in siren
Z-Wave Protocol: Z-Wave Plus 500, 868.40MHz (EU)
RF Frequency: 868MHz
Power supply: 12V, 1A
Battery back-up: 7.2V, 1100mAh, Ni-mH, rechargeable
Battery life 13 hours
Operating temperature -10°C ~ +45°C
Relative humidity: Up to 85% (non-condensing)
Dimensions: 140 (W) x 150 (H) x 42 mm
Certified EN50131 Grade 2, Environmental Class II
The VESTA radio control unit is compatible with Google Home and Alexa