

VESTA-411

RC-16-AMX

ALARM.COM

4-button radio pushbutton

✓ GRADE 2

- Radio push button with 4 buttons
- Arm/disarm, start and panic
- Suitable for security and home automation
- Operates with 1 CR2032 3V lithium battery
- Battery life of 8 years
- EN50131 Grade 2, Class II



Reference / Model

VESTA-411 / RC-16-AMX

Allows control of the security system

Four buttons: Arming / Disarming / Home / Panic

Durable and scratch resistant buttons

Lightweight keychain design

Low battery detection

Suitable for security and home automation installations

RF Frequency: 868MHz

Power supply: 1 CR2032 3V lithium battery

Battery life of 8 years

Operating temperature from -10°C ~ +45°C

Relative humidity up to 85% (non-condensing)

Dimensions: 33.8 (W) x 51.08 (H) x 14.24 mm

EN50131 Grade 2, Class II certified