

VESTA-177-BLACK

IR-35SL-F1-2W



VESTA Radio PIR Detector



- PIR detector via radio VESTA
- Coverage 15 meters, 130°
- Anti-pet 45 kg (remote configurable)
- Automatic calibration of the PIR sensor
- Double detection function configurable from Installer App
- 2 levels of sensitivity (configurable remotely)
- Efficient rest time between detections
- Optional swivel bracket
- Works with 1 CR123 battery
- Battery life of 5.8 years
- Black color
- Grade 2 certified



Reference / Model

VESTA-177-BLACK / IR-35SL-F1-2W

Detection range: 15 meters, 130°.

Automatic PIR sensor calibration

Dual detection function available (alarm is acknowledged in case of two detections in a short time), configurable from installer's App

Efficient sleep time between detections

RF frequency: 868MHz

Microprocessor controlled with advanced ADSP algorithms for false alarm immunity

Anti-pet up to 45 kg

Two selectable sensitivity levels

Remote configurable sensor sensitivity and anti-pet function

High false alarm immunity

Tamper protection against tampering

Superior white light and noise rejection

VESTA-177-BLACK

IR-35SL-F1-2W



VESTA Radio PIR Detector

Reference / Model	VESTA-177-BLACK / IR-35SL-F1-2W
	Automatic power saving mechanism
	Random monitoring signals for system integrity
	Radio interference rejection
	Sensitivity control with temperature compensation
	Powered by 1 CR123 battery
	Battery life of 5.8 years
	Operating temperature -10°C ~ +45°C (-10°C ~ +45°C)
	Relative humidity up to 85% (non-condensing)
	Black color
	Installation height 2.3 ~ 2.5 meters (8 ~ 8.5 feet)
	Optional swivel mount
	Grade 2 certified