F1 wired and wireless keypad

✅ GRADE 3

- F1 wired and radio keypad for VESTA 4G Alarm.com hybrid system
- Incorporates 97dB siren
- Up to 4 keypads per system
- 4 wires via RS485, up to 150 meters
- For programming of hybrid control panels
- EN50131 Grade 3 certified

Reference / Model	VESTA-406 / KP-35-COMBO ADC
Wired and wireless keypad only compatible with Alarm.com 4G hybrid control panel.	
Installer and user menus for setup and configuration	
32-character LCD display	
Memory of alarms, event logs, fault reports or system status reports	
Built-in siren for sounding alarm sounds	
Audible beeps to indicate entry/exit delays and other system statuses	
Illuminated keypad and LCD display for optimum visibility in darkness	
Dual key function for activation of panic, fire or medical emergency alarms	
Periodic supervisory signals to check system integrity	
Easy installation with both wall and desktop mounting options	
4-wire connection via RS-485, up to 150 meters (500 feet)	
Up to 4 wired keypads per system	
Wall tamper tamper	

F1 wired and wireless keypad

Reference / Model	VESTA-406 / KP-35-COMBO ADC
Nominal voltage 12V DC	
Power supply in radio mode: 2 x 1.5V AA L91 lithium batteries (not included)	
RF frequency: F1 868 MHz	
Operating temperature -10°C ~ +45°C (-10°C ~ +45°C)	
Operating humidity 85% at 23°C (non-condensing)	
Dimensions: 143 x 115 x 28.5 mm	
Weight: 244.5 g	
EN50131 Grade 3 certified	